

Correlator Bank Detection of GW chirps. False-Alarm Probability, Template Density and Thresholds: Behind and Beyond the Minimal-Match Issue.

R.P. Croce,¹ Th. Demma,¹ M. Longo,² S. Marano,² V. Matta,² V. Pierro,¹ and I.M. Pinto¹

¹*Wavesgroup, University of Sannio at Benevento, Italy*

²*DIIE, University of Salerno, Italy*

(Dated:)

The general problem of computing the false-alarm rate vs. detection-threshold relationship for a bank of correlators is addressed, in the context of maximum-likelihood detection of gravitational waves, with specific reference to chirps from coalescing binary systems. Accurate (lower-bound) approximants for the cumulative distribution of the whole-bank supremum are deduced from a class of Bonferroni-type inequalities. The asymptotic properties of the cumulative distribution are obtained, in the limit where the number of correlators goes to infinity. The validity of numerical simulations made on small-size banks is extended to banks of any size, via a gaussian-correlation inequality. The result is used to estimate the optimum template density, yielding the best tradeoff between computational cost and detection efficiency, in terms of undetected potentially observable sources at a prescribed false-alarm level, for the simplest case of Newtonian chirps.

PACS numbers:

I. INTRODUCTION.

In the next few years a number of optical-interferometric detectors of gravitational waves will be in operation [1]-[4], supplying steady fluxes of data to be sieved in the search of gravitational wave (henceforth GW) signatures of astrophysical origin. Among expected signals, those of *known* shape, except for the *values* of a set of parameters which embody the relevant information on the source physics, are specially valuable to perspective gravity wave astronomy [5]. The maximum-likelihood strategy for detecting signals of known shape in additive stationary gaussian colored noise [6] consists in projecting the data on a finite discrete set of expected waveforms (the so called *templates*), and using the largest projection Λ for computing a detection statistic. The detection statistic Λ is a random variable. Letting

$$F_{\Lambda}(x) = \text{Prob}[\Lambda \leq x | \text{no signal}], \quad (1.1)$$

it is possible to determine uniquely a *threshold* γ such that:

$$\text{Prob}[\Lambda > \gamma | \text{no signal}] = 1 - F_{\Lambda}(\gamma) = \alpha \quad (1.2)$$

where α is a *prescribed* false-alarm probability. The detection algorithm accordingly consists in comparing the detection statistic Λ to the threshold γ . Whenever $\Lambda > \gamma$ one declares that a signal has been observed at the false-alarm level α . The unknown source parameters are then *estimated* from those of the template yielding the largest projection. Deriving an *exact* (or suitably approximate) representation of the distribution function $F_{\Lambda}(x)$ is clearly a key problem for detector's efficiency optimization. In this paper we present a thorough analysis and a possible working solution of this problem, for the special relevant case of gravitational wave chirps from coalescing binary stars. In particular, we present the formal deduction of several partial results anticipated in [7],[8]. As a by-product, previous findings by Dhurandhar, Schutz, Krolak and Mohanty [9]-[12] are recovered and hopefully generalized. The paper is organized as follows. In Sect. II, gravitational wave chirp templates and correlators are introduced, the minimal match is defined, and the statistical covariance among different correlators is computed, for the special relevant case where no signal is present in the data. This section is included to make the paper self-contained and to fix the notation, and could perhaps be skipped by the expert Reader. In Sect. III, the minimal-match issue is reviewed, and the interplay between template density, detection threshold and detector's efficiency (fraction of detected events among those potentially observable) is discussed. The study of (1.1) is undertaken in Sect. IV. Available results are first reviewed. A number of accurate lower-bound (conservative) *approximants* of $F_{\Lambda}(x)$ are then discussed. The abstract asymptotic properties of $F_{\Lambda}(x)$ in the limit where the number of correlators $N \rightarrow \infty$ are next highlighted. It is finally shown that one can capitalize on a classical inequality to extend the validity of numerical simulations made on moderate-size template banks to banks of arbitrary (large) size. In Sect. V the minimal-match issue is reconsidered, in the light of results obtained in previous sections. The main conclusion is that, in contrast to common belief, increasing the template density in parameter space beyond a certain limiting value does *not* improve the detector's performance (fraction

of detected events among those potentially observable) in any significant fashion. It is pointed out that in order to estimate the above limiting value, the accuracy of the no-signal cumulative distribution (1.1) is a key ingredient. Conclusions and recommendations follow under Sect. VI.

The core results of this paper (especially those in Sect. IV) rely on a number of rather technical arguments, which are collected in Appendix A and B.

II. CHIRP TEMPLATES AND CORRELATORS

The (spectral) projection of the data $A(f)$ on a template $T(f)$ is the (antenna noise-weighted) scalar product:

$$\langle A, T \rangle = 2\text{Re} \left\{ \int_{f_i}^{f_s} \frac{df}{\Pi(f)} A(f) T^*(f) \right\}, \quad (2.1)$$

also called the *correlator* between A and T . In (2.1), $A(f) = S(f) + N(f)$, where $S(f)$ is a (possibly null) signal, $N(f)$ is a realization of the antenna noise, (f_i, f_s) is the useful antenna spectral window, $\Pi(f)$ is the antenna noise power spectral density, and $*$ denotes complex conjugation.

The stationary-phase asymptotic representation of a post-newtonian chirp waveform can be written [13]:

$$H(f, \phi, \tau, \vec{\xi}) = H_0 f^{-7/6} \exp \left\{ j \left[2\pi f \tau - \phi + \psi(f, \vec{\xi}) \right] \right\}, \quad (2.2)$$

where H_0 is a (complex, unknown) constant, depending on the source position and (relative) antenna orientation, τ is the nominal coalescency time [14], ϕ is the phase at $t = \tau$ and $\psi(f, \vec{\xi})$ is a function of the *intrinsic* source parameters only (i.e., the binary companion masses and spin parameters), represented by the vector $\vec{\xi}$. Equation (2.2) is used to model the sought signal as well as to construct the templates. Suffixes S and T will be used, when needed, to identify the signal and template, respectively. Templates are usually constructed with unit norm, viz.:

$$H_{0T} = \left[2 \int_{f_i}^{f_s} f^{-7/3} \frac{df}{\Pi(f)} \right]^{-1/2} \iff \|T\| = \langle T, T \rangle^{1/2} = 1. \quad (2.3)$$

The maximum-likelihood detection statistic is (any monotonically increasing function of):

$$\Lambda = \sup_{\vec{\xi}_T} \sup_{\tau_T} \sup_{\phi_T} \langle A, T \rangle, \quad (2.4)$$

where the supremums are taken on the set of available templates.

The correlators (2.1) can be readily maximised w.r.t. the irrelevant parameter ϕ_T , yielding:

$$c[A, T] = \sup_{\phi_T} \langle A, T \rangle = \frac{\left| 2 \int_{f_i}^{f_s} A(f) f^{-7/6} e^{-j[2\pi f \tau_T + \psi(f, \vec{\xi}_T)]} \frac{df}{\Pi(f)} \right|}{\left[2 \int_{f_i}^{f_s} f^{-7/3} \frac{df}{\Pi(f)} \right]^{1/2}}. \quad (2.5)$$

The r.h.s. of (2.5) is called the *noncoherent correlator*. In view of eq. (2.5) all templates can be generated with $\phi_T = 0$. The integral in (2.1) is then recognized (but for inessential factors) as the $f \rightarrow \tau_T$ Fourier transform of the function:

$$K_A(f, \vec{\xi}_T) = \begin{cases} 2 \frac{A(f) T^*(f, 0, 0, \vec{\xi}_T)}{\Pi(f)}, & f \in (f_i, f_s) \\ 0, & \text{elsewhere.} \end{cases} \quad (2.6)$$

One is therefore led to construct a family of *reduced templates* with $\phi_T = \tau_T = 0$, parameterized in $\vec{\xi}_T$. Further maximisation of the noncoherent correlator (2.5) w.r.t. τ_T can thus be accomplished by taking the largest absolute value of the $f \rightarrow \tau_T$ Fourier transform of (2.6). The resulting quantity

$$C[A, T] = \sup_{\tau_T} c[A, T] = \sup_{\tau_T} \sup_{\phi_T} \langle A, T \rangle = \sup_{\tau} \left| \mathcal{F}_{f \rightarrow \tau} [K_A(f, \vec{\xi}_T)] \right| \quad (2.7)$$

is called the *reduced* noncoherent correlator, and is a function of the *intrinsic* source and template parameters only. The detection statistic can thus be written

$$\Lambda = \sup_{\vec{\xi}_T} C[A, T]. \quad (2.8)$$

A. The Minimal-Match Prescription

The similarity (matching) between a signal $S(f)$ and a (non reduced) template $T(f)$ is measured by their *overlap*,

$$\mathcal{O}[S, T] = \frac{\langle S, T \rangle}{\|S\| \cdot \|T\|} \leq 1 \quad (2.9)$$

where the norm is defined in eq. (2.3).

Given a (discrete) family of templates $\mathcal{L}$, and a set $\mathcal{S}$ of admissible signals, the quantity

$$FF(\mathcal{L}, \mathcal{S}) = \inf_{S \in \mathcal{S}} \sup_{T \in \mathcal{L}} \mathcal{O}[S, T] \quad (2.10)$$

is called the fitting-factor between $\mathcal{L}$ and $\mathcal{S}$ [15].

The probability of detecting (at any *fixed* false-alarm level) a known signal $S(f)$ hidden in the noisy (spectral) data $A(f)$ using $\langle A, T \rangle$ as a detection statistic is an increasing function [15] of the overlap $\mathcal{O}[S, T]$. Thus, given $\mathcal{S}$, the (discrete, non-reduced) template family $\mathcal{L}$ is designed in such a way that

$$FF(\mathcal{L}, \mathcal{S}) \geq \Gamma, \quad (2.11)$$

where the physical meaning of Γ will be discussed in Sect. III. It is convenient to define the function

$$M[S, T] = \sup_{\tau_T} \sup_{\phi_T} \mathcal{O}[S, T] \quad (2.12)$$

called the match between S and T [16], and to rephrase (2.11) as follows:

$$\forall S \in \mathcal{S}, \exists T \in \mathcal{L} : M[S, T] \geq \Gamma. \quad (2.13)$$

The quantity Γ is referred to as the *minimal match*.

The match can be readily computed in terms of the *reduced* templates and waveforms:

$$M[S, T] = \left[\int_{f_i}^{f_s} f^{-7/3} \frac{df}{\Pi(f)} \right]^{-1} \sup_{\tau} \left| \mathcal{F}_{f \rightarrow \tau} [K_S(f, \vec{\xi}_T)] \right|, \quad (2.14)$$

where, from eq. (2.2)

$$K_S(f, \vec{\xi}_T) = \begin{cases} \frac{f^{-7/3} e^{j[\psi(f, \vec{\xi}_S) - \psi(f, \vec{\xi}_T)]}}{\Pi(f)}, & f \in (f_i, f_s) \\ 0, & \text{elsewhere.} \end{cases} \quad (2.15)$$

More or less obviously,

$$\forall \vec{\xi}_S, \vec{\xi}_T, \quad 0 < M[S, T] \leq 1, \quad (2.16)$$

the equality holding iff $S = T$.

B. The (Reduced) Template Lattice

We shall assume the reduced waveforms/templates to be parameterized in such a way that $\psi(f, \vec{\xi}_S) - \psi(f, \vec{\xi}_T)$ is a function of the *difference* $\vec{\xi}_S - \vec{\xi}_T$ only [17]. Under this assumption, to leading order in the (small) difference $\vec{\xi}_S - \vec{\xi}_T$, the match can be cast in the form [16]:

$$M[S, T] \approx 1 - (\vec{\xi}_S - \vec{\xi}_T)^2 \quad (2.17)$$

and the minimal-match condition becomes:

$$\forall \vec{\xi}_S \in \mathcal{S}', \exists \vec{\xi}_T \in \mathcal{L}' : (\vec{\xi}_S - \vec{\xi}_T)^2 \leq 1 - \Gamma, \quad (2.18)$$

where $\mathcal{S}' \subset \mathcal{S}$ and $\mathcal{L}' \subset \mathcal{L}$ are the sub-manifolds corresponding to $\phi = \tau = 0$. The ball

$$\Sigma_k = \{\vec{\xi}_S : (\vec{\xi}_S - \vec{\xi}_k)^2 \leq 1 - \Gamma\} \quad (2.19)$$

is called the *span* of $T_k = T(\vec{\xi}_k)$ at the minimal-match level Γ , and the minimal-match prescription is further rephrased as:

$$\bigcup_k \Sigma_k \supseteq \mathcal{S}'. \quad (2.20)$$

In the simplest case, the $\vec{\xi}_k$ can be chosen to form a cubical lattice [18]. Then, the distance between nearest-neighbour reduced templates (cubical-cell sidelength) is

$$\Delta = 2 \left(\frac{1 - \Gamma}{P} \right)^{1/2} \quad (2.21)$$

where P is the dimension of $\vec{\xi}$. Hence, the template density is Δ^{-P} , and the template number N_Δ is of the order of the volume of $\mathcal{S}'$ divided by the elementary cell volume Δ^P .

C. The Pure-Noise Case Correlator Covariance Matrix

In deducing the (no-signal) cumulative distribution of the whole-bank supremum it is expedient to deal with the following *squared* quantities:

$$Z = \frac{c^2}{2}, \quad \mathcal{Z} = \frac{C^2}{2}, \quad X = \frac{\Lambda^2}{2}, \quad (2.22)$$

in view of the exponential (no-signal) distribution of the random variable Z . The sought transformation does not affect detector performances, X being an *equivalent* sufficient detection statistic. Equations (2.22) will be used systematically throughout. Letting

$$\begin{aligned} Y(\tau, \vec{\xi}) &=: \frac{\int_{f_i}^{f_s} N(f) f^{-7/6} e^{-j[2\pi f\tau + \psi(f, \vec{\xi})]} \frac{df}{\Pi(f)}}{\left[\int_{f_i}^{f_s} f^{-7/3} \frac{df}{\Pi(f)} \right]^{1/2}} = \\ &= \left[\int_{f_i}^{f_s} f^{-7/3} \frac{df}{\Pi(f)} \right]^{-1/2} \mathcal{F}_{f \rightarrow \tau} [K_N(f, \vec{\xi})], \end{aligned} \quad (2.23)$$

where

$$K_N(f, \vec{\xi}) = \begin{cases} \frac{N(f) f^{-7/6} e^{-j\psi(f, \vec{\xi})}}{\Pi(f)}, & f \in (f_i, f_s) \\ 0, & \text{elsewhere,} \end{cases} \quad (2.24)$$

one readily gets, in view of eq.s (2.5) and (2.22):

$$Z = |Y(\tau, \vec{\xi})|^2, \quad \mathcal{Z} = \sup_\tau |Y(\tau, \vec{\xi})|^2, \quad X = \sup_{\vec{\xi}} \sup_\tau |Y(\tau, \vec{\xi})|^2. \quad (2.25)$$

The noise being assumed as stationary zero-mean colored gaussian, $Y(\tau, \vec{\xi})$ is a zero-average *complex gaussian random field*. It is therefore completely characterized by its second-order joint expectation value (covariance), viz.:

$$E[Y(\tau, \vec{\xi})Y^*(\tau', \vec{\xi}')] = \frac{\int_{f_i}^{f_s} f^{-7/3} e^{-j\{2\pi f(\tau-\tau') + [\psi(f, \vec{\xi}) - \psi(f, \vec{\xi}')] \}} \frac{df}{\Pi(f)}}{\int_{f_i}^{f_s} f^{-7/3} \frac{df}{\Pi(f)}}. \quad (2.26)$$

It is readily seen that:

$$\left| E[Y(\tau, \vec{\xi})Y^*(\tau', \vec{\xi}')] \right| = \frac{c[T, T']}{\|T\| \cdot \|T'\|}. \quad (2.27)$$

D. Discrete Implementation

Let N_Δ the total number of reduced templates used to cover $\mathcal{S}'$. Each reduced template yields as many (non-coherent) correlators as the number of time bins in the discrete Fourier transform (henceforth DFT [19]) used to compute numerically eq. (2.5). The above number will be denoted by N_Θ . The detection statistic is thus:

$$\Lambda = \max_{k \in [1, N_\Delta]} \max_{h \in [1, N_\Theta]} \left| DFT_h[K_A(f, \vec{\xi}_k)] \right|, \quad (2.28)$$

where the integers h and k span the DFT output time bins, denoted as $DFT_h[\cdot]$, and the (discrete) reduced template family, respectively.

The match between a signal S and a template T is computed as

$$M[S, T] = \max_{h \in [1, N_\Theta]} \frac{\left| DFT_h[K_S(f, \vec{\xi}_k)] \right|}{\left| \int_{f_i}^{f_s} f^{-7/3} \frac{df}{\Pi(f)} \right|}. \quad (2.29)$$

As an effect of time-discretization, $M[S, S]$ computed with (2.29) can be less than one. The DFT time step (and length) should be accordingly chosen in such a way that

$$\forall S \in \mathcal{S}', \quad 1 - M[S, S] \ll 1 - \Gamma. \quad (2.30)$$

We define the following zero-average gaussian random suite, which is the discrete counterpart of eq. (2.23)

$$Y_{h,k} = \left[\int_{f_i}^{f_s} f^{-7/3} \frac{df}{\Pi(f)} \right]^{-1/2} DFT_h[K_N(f, \vec{\xi}_k)], \quad h = 1, 2, \dots, N_\Theta, \quad k = 1, 2, \dots, N_\Delta, \quad (2.31)$$

which is completely characterized by the covariance matrix

$$\sigma(k - h, \vec{\xi}_n - \vec{\xi}_m) = E[Y_{h,m} Y_{k,n}^*]. \quad (2.32)$$

We note that $\sigma(0, \vec{0}) = 1$ by construction, and further define

$$\rho_M = \max |\sigma(q, \vec{\xi}_n - \vec{\xi}_m)|, \quad (q, \vec{\xi}_n - \vec{\xi}_m) \neq (0, \vec{0}). \quad (2.33)$$

Note that, in view of eq. (2.30) one has

$$\rho_M = |\sigma(1, \vec{0})| \quad (2.34)$$

which means that the largest (absolute) covariance always occurs between correlators differing only in τ by a single DFT time bin.

III. MINIMAL MATCH VS. UNDETECTED OBSERVABLE SOURCES

The minimal match is more or less obviously related to the *fraction* of potentially observable sources which would be undetected as an effect of template mismatch. It was first argued in [15] that (under the simplest assumption of isotropically and homogeneously distributed sources) this latter would be simply $(1 - \Gamma^3)$.

In order to gain insight into this issue, it is expedient to work in terms of the detection probability P_d . Accordingly, let

$$P_d = 1 - \beta = 1 - Q[\gamma - E(\Lambda)] \quad (3.1)$$

where $Q(\cdot)$ is an unknown CDF, whose density can be nonetheless safely assumed as being unimodal and center-symmetric, at least for meaningful values of the signal-to-noise ratio. In the worst case of *minimal* match,

$$E(\Lambda) \approx \Gamma d, \quad (3.2)$$

where d is the signal deflection (signal-to-noise ratio), viz.:

$$d := \left| 2 \int_{f_i}^{f_s} \frac{S(f)S^*(f)}{\Pi(f)} df \right|^{1/2}, \quad (3.3)$$

and we assume $d \gg 1$. Let the *observable* sources be those for which $P_d \geq 0.5$. Under the above assumptions for $Q(\cdot)$, these correspond to:

$$d \geq \frac{\gamma}{\Gamma}. \quad (3.4)$$

The deflection d on the other hand can be written

$$d = \frac{K}{R} \quad (3.5)$$

where R is the source distance, and K is a constant depending on the antenna and source features, as well as their mutual orientation. Equation (3.4) allows to define the radius R of the antenna-centered sphere which contains all observable sources of a given class (seen by the same antenna, sharing the same features and orientation), viz.:

$$R = \frac{K\Gamma}{\gamma}. \quad (3.6)$$

Hence the number of *observable* sources in the given class, under the most obvious hypothesis of uniform (homogeneous and isotropic) spatial source density ρ_s is:

$$N_s = \frac{4}{3}\pi\rho_s \left[\frac{K\Gamma}{\gamma} \right]^3. \quad (3.7)$$

Letting Γ_{max} , N_{max} the largest achievable minimal match, and the related number of templates, and denoting as $N_s^{(max)}$ the corresponding value of N_s , one has from (3.7):

$$\eta = \frac{N_s}{N_s^{(max)}} = \left(\frac{\Gamma}{\Gamma_{max}} \right)^3 \left(\frac{\gamma(\alpha, N_{max})}{\gamma(\alpha, N)} \right)^3 \quad (3.8)$$

where the dependence of γ from α and N (and hence on Γ itself) has been written explicitly. The quantity $1 - \eta$ represents the fraction of *observable* sources which would be lost due to poor minimal match ($\Gamma < \Gamma_{max}$). Note that the ratio η does *not* depend on K .

Neglecting the dependence of γ on N , the second factor on the r.h.s. of (3.8) cancels, and we are left with

$$\eta = \left(\frac{\Gamma}{\Gamma_{max}} \right)^3 := \eta_0, \quad (3.9)$$

which does *not* depend on α . Under the same assumption, N_s in (3.7) increases monotonically with Γ , attaining its supremum $N_s^{(max)}$ at $\Gamma_{max} = 1$, yielding $\eta_0 = \Gamma^3$. This is, in essence, the simplest argument introduced in [15].

This argument conceals an obvious naivety insofar as it neglects the dependence of the detection threshold γ corresponding to a given false-alarm probability α on the total number of templates $N = N_\Theta N_\Delta$, and hence on Γ itself.

In order to refine this reasoning one should fully take into account the dependence of γ on N , which in turn is affected by the covariance among the correlators. We shall postpone the relevant results of such a refined analysis until the end of Sect. V, after having introduced the needed no-signal CDF of the detection statistic Λ , which is the subject of the next section.

IV. NO-SIGNAL WHOLE-BANK STATISTICS

In order to provide a "working" solution to the problem of computing the whole-bank false-alarm probability, we should be able in principle:

- to provide a hopefully decent *approximant* of F_X ;
- to guarantee that the above approximant is otherwise a *lower bound* for the *true* CDF, so that one makes a conservative error while using it to compute the threshold corresponding to a given false-alarm probability;
- to formulate a criterion whereby the validity of simulations made on relatively small-sized banks could be extended to huge (real-world) banks, for which direct numerical simulations are either unwieldy or unfeasible.

To make the dependence of $F_X(x)$ on the number N of templates explicit, we shall denote it in this section by

$$F_X^{(N)}(x) = \text{Prob}[X \leq x | \text{no signal}]. \quad (4.1)$$

A. Background

In the ideal case where the correlators are statistically independent, one has simply:

$$F_X^{(N)}(x) = [1 - \exp(-x)]^N =: \Phi_X^{(N)}(x). \quad (4.2)$$

In all practical cases, the covariance among the correlators is nonzero, and hence the independent-correlator formula (4.2) is poorly accurate. However, in Appendix A we prove that, for any finite N and any x , the independent-correlator approximation $\Phi_X^{(N)}$ is a *lower bound* for $F_X^{(N)}$, viz.:

$$F_X^{(N)} \geq \Phi_X^{(N)}, \quad (4.3)$$

thus implying a *conservative* error (for any fixed threshold it gives a lower false alarm rate).

It was first suggested by Dhurandhar and Schutz [9] that eq. (4.2) can be made more accurate after *reducing* N by a suitable factor $\epsilon \in [0, 1[$. Extensive numerical simulations supporting this suggestion were subsequently reported in [10] by Dhurandhar and Mohanty [20]. In Jaranowski et al. [11] it was heuristically argued that

$$\epsilon \approx \frac{\mu(\eta_T)}{\mu(\eta_c)} \quad (4.4)$$

where $\mu(\eta_T)$, $\mu(\eta_c)$ are the measures of the *span* and *correlation neighbourhood* [21] of a template, respectively [11], which are both functions of the prescribed minimal match Γ . In [12] Mohanty introduced an elegant formal argument whereafter an approximate closed-form expression for ϵ could be derived [22]. Mohanty's argument is based on the following key assumptions, valid for *suitably large* values of the threshold:

- i) that *at most two* (squared) correlators, say Z , Z' can simultaneously exceed the threshold x , and
- ii) that the corresponding templates can only be nearest-neighbours, featuring the largest (absolute) covariance. As already noted, the largest (absolute) covariance ρ_M occurs between $Y_{i,j}$ and $Y_{i+1,j}$, so that Mohanty's argument applies naturally to the cumulative distribution of each and any reduced noncoherent correlator $\mathcal{Z}$.

Hence [23],

$$F_{\mathcal{Z}}^{(N_{\Theta})}(x) \approx 1 - N_{\Theta} \text{Prob}[Z_{i,j} > x | \text{no signal}] + (N_{\Theta} - 1) \text{Prob}[Z_{i,j} > x, Z_{i+1,j} > x | \text{no signal}]. \quad (4.5)$$

This can be used to obtain the mentioned ϵ factor by comparison with

$$F_{\mathcal{Z}}^{(N_{\Theta})}(x) \approx [1 - \exp(-x)]^{\epsilon N_{\Theta}} \approx 1 - \epsilon N_{\Theta} \exp(-x), \quad (4.6)$$

(binomial approximation, large thresholds) yielding:

$$\epsilon \approx 1 - (1 - N_{\Theta}^{-1}) \text{Prob}[Z_{i+1,j} > x | Z_{i,j} > x, \text{no signal}]. \quad (4.7)$$

The above quoted results do not allow to make any rigorous statement insofar as the behaviour of $F_X^{(N)}$ is concerned for *large* N and/or large thresholds (beyond values for which numerical checking is feasible). In addition it is not clear whether using (4.5) gives a conservative estimate of the threshold.

B. Mohanty's formula as a lower bound

In this section we derive Mohanty's formula following a different route, whose validity does *not* rest on any of the *ad hoc* hypotheses made in [12]. We shall further prove that Mohanty's formula is in fact a CDF lower bound.

We start from the following *Bonferroni-type* inequality [24]:

$$\begin{aligned} \text{Prob} \left[\bigcup_{i=1}^N E_i \right] &= \text{Prob} \left[\bigcup_{i=1}^{N-1} (E_i - E_i \cap E_{i+1}) \cup E_N \right] \leq \\ &\leq \sum_{i=1}^{N-1} \text{Prob}[E_i - E_i \cap E_{i+1}] + \text{Prob}[E_N] = \sum_{i=1}^N \text{Prob}[E_i] - \sum_{i=1}^{N-1} \text{Prob}[E_i \cap E_{i+1}], \end{aligned} \quad (4.8)$$

which holds for arbitrary *events* $\{E_i\}_{i=1}^N$. Equation (4.8) can be used to derive several lower bounds for the cumulative distribution of the *reduced* noncoherent correlator $\mathcal{Z}$. Indeed, letting $E_i = \{Z_{i,j} > x\}$, $i = 1, 2, \dots, N_{\Theta}$, where $j \in (1, 2, \dots, N_{\Delta})$ is fixed, one gets:

$$\begin{aligned} F_{\mathcal{Z}}^{(N_{\Theta})}(x) &= 1 - \text{Prob}[\max_{i=1, \dots, N_{\Theta}} Z_{i,j} > x | \text{no signal}] \geq 1 - \sum_{i=1}^{N_{\Theta}} \text{Prob}[Z_{i,j} > x | \text{no signal}] + \\ &+ \sum_{i=1}^{N_{\Theta}-1} \text{Prob}[Z_{i,j} > x, Z_{i+1,j} > x | \text{no signal}]. \end{aligned} \quad (4.9)$$

Equation (4.9) yields different lower bounds, depending on the way the templates are indexed. The tightest bound is obtained whenever the indexing is such that *consecutive* templates in (4.9) exhibit the *largest* covariance. In view of eq. (2.30) this occurs invariably between templates corresponding to the same *intrinsic* parameters, and differing only by a single time-discretization bin in τ [25].

Taking into account the stationarity of the sequence $Z_{i,j}$, eq. (4.9) can be cast in the form:

$$F_{\mathcal{Z}}^{(N_{\Theta})}(x) \geq 1 - N_{\Theta} \text{Prob}[Z_{i,j} > x | \text{no signal}] + (N_{\Theta} - 1) \text{Prob}[Z_{i,j} > x, Z_{i+1,j} > x | \text{no signal}]. \quad (4.10)$$

Both probability terms in (4.10) can be evaluated explicitly, as shown in detail e.g. in [26], yielding:

$$\text{Prob}[Z_{i,j} > x | \text{no signal}] = \exp(-x), \quad (4.11)$$

and

$$\text{Prob}[Z_{i,j} > x, Z_{i+1,j} > x | \text{no signal}] = (1 - \rho_M^2) \sum_{k=0}^{\infty} \frac{\rho_M^{2k} \Gamma_E^2[k+1, (1 - \rho_M^2)^{-1}x]}{\Gamma_E^2(k+1, 1)}, \quad (4.12)$$

where $\Gamma_E(\cdot, \cdot)$ is the incomplete Euler gamma function [27]. Equation (4.10) can be conveniently written in a more compact form as:

$$F_{\mathcal{Z}}^{(N_{\Theta})}(x) \geq 1 - N_{\Theta} \exp(-x) \epsilon(N_{\Theta}, x, \rho_M), \quad (4.13)$$

where:

$$\epsilon(N_{\Theta}, x, \rho_M) = 1 - (1 - N_{\Theta}^{-1}) \exp(x) (1 - \rho_M^2) \sum_{k=0}^{\infty} \frac{\rho_M^{2k} \Gamma_E^2[k+1, (1 - \rho_M^2)^{-1}x]}{\Gamma_E^2(k+1, 1)}. \quad (4.14)$$

Comparison of (4.14) with Mohanty's formula (4.7) reveals that this latter gives a *lower bound* [28] of $F_{\mathcal{Z}}^{(N_{\Theta})}$.

In principle, inequality (4.8) can be used to derive lower bounds for the cumulative distribution of the whole-bank supremum $F_X^{(N)}$ as well. For the sake of simplicity, we refer to the case of Newtonian templates, featuring a single *intrinsic* parameter, namely the chirp mass. Under this assumption, the $N = N_{\Theta} N_{\Delta}$ correlators can be conveniently cast in lexicographic order:

$$Z_{i,j} \rightarrow Z_{i+(j-1)N_{\Theta}}, \quad i = 1, 2, \dots, N_{\Theta}, \quad j = 1, 2, \dots, N_{\Delta}. \quad (4.15)$$

From (4.15) and Fig. 1, it is seen that there exist $N_{\Delta} - 1$ consecutive correlator pairs whose covariances are negligible. It turns out that the relevant number of correlator pairs exhibiting the maximum (absolute) covariance ρ_M is $N_{\Theta} N_{\Delta} - (N_{\Delta} - 1) - 1$. Accordingly, letting $E_i = \{Z_i > x\}$ in equation (4.8) gives:

$$\begin{aligned} F_X^{(N)}(x) &= 1 - \text{Prob}[\max_i Z_i > x | \text{no signal}] \geq 1 - \sum_{i=1}^{N_{\Theta} N_{\Delta}} \text{Prob}[Z_i > x | \text{no signal}] + \\ &+ \sum_{i=1}^{N_{\Theta} N_{\Delta} - N_{\Delta}} \text{Prob}[Z_i > x, Z_{i+1} > x | \text{no signal}], \end{aligned} \quad (4.16)$$

where the meaning of Z_i is obvious from (4.15). Equation (4.16) is conveniently rephrased as:

$$F_X^{(N)}(x) \geq 1 - N_{\Theta} N_{\Delta} \exp(-x) \epsilon(N_{\Theta}, x, \rho_M). \quad (4.17)$$

C. Nested Mohanty's Formula

Inequality (4.8) can be notably invoked *recursively* to provide hopefully more accurate lower bounds for the CDF of the supremum of the *whole* bank of (squared noncoherent) correlators. Indeed, letting $E_j = \{\mathcal{Z}_j > x\}$, $j = 1, 2, \dots, N_{\Delta}$ in (4.8), we obtain:

$$\begin{aligned} F_X^{(N)}(x) &= 1 - \text{Prob}[\max_j \mathcal{Z}_j > x | \text{no signal}] \geq \\ &\geq 1 - \sum_{j=1}^{N_{\Delta}} \text{Prob}[\mathcal{Z}_j > x | \text{no signal}] + \sum_{j=1}^{N_{\Delta}-1} \text{Prob}[\mathcal{Z}_j > x, \mathcal{Z}_{j+1} > x | \text{no signal}]. \end{aligned} \quad (4.18)$$

Again, by statistical uniformity and stationarity,

$$F_X^{(N)}(x) \geq 1 - N_{\Delta} \text{Prob}[\mathcal{Z}_j > x | \text{no signal}] \cdot \{1 - (1 - N_{\Delta}^{-1}) \text{Prob}[\mathcal{Z}_{j+1} > x | \mathcal{Z}_j > x, \text{no signal}]\}, \quad (4.19)$$

for any j . One can use eq. (4.13) in (4.19), to obtain

$$F_X^{(N)}(x) \geq 1 - N_{\Delta} N_{\Theta} \exp(-x) \epsilon(N_{\Theta}, x, \rho_M) \cdot \{1 - (1 - N_{\Delta}^{-1}) \text{Prob}[\mathcal{Z}_{j+1} > x | \mathcal{Z}_j > x, \text{no signal}]\}. \quad (4.20)$$

There is *no* simple recipe for computing the conditional probability in (4.20). However one might speculate that

$$\text{Prob}[\mathcal{Z}_{j+1} > x | \mathcal{Z}_j > x, \text{no signal}] \geq \text{Prob}[Z_{i,j+1} > x | Z_{m,j} > x, \text{no signal}], \quad (4.21)$$

for any $i \in (1, 2, \dots, N_\Theta)$ and any $j \in (1, 2, \dots, N_\Delta - 1)$, where $m \in (1, 2, \dots, N_\Theta)$ is defined by the condition [29]

$$\rho'_M = |E[Y_{i,j+1}Y_{m,j}^*]| > |E[Y_{i,j+1}Y_{h,j}^*]|, \quad \forall h \neq m. \quad (4.22)$$

Under this assumption, equation (4.20) yields:

$$F_X^{(N)}(x) \geq 1 - N_\Delta N_\Theta \exp(-x) \epsilon(N_\Theta, x, \rho_M) \epsilon(N_\Delta, x, \rho'_M). \quad (4.23)$$

Equation (4.23) can be readily generalized to post-newtonian intrinsic parameter spaces of dimension higher than one, by iterating the above reasoning. It is also recognized that eq. (4.17) corresponds to neglecting the covariance between reduced templates in (4.23).

D. Asymptotics

We shall now discuss the asymptotic form of $F_X^{(N)}$ as $N \rightarrow \infty$. This question is properly dealt with in the frame of extreme-value theory (henceforth EVT). Note that the study of the above asymptotics via numerical simulation is almost impossible (the tail behaviour requires a huge number of simulations) unless some a-priori information is available.

The EVT philosophy can be understood intuitively by noting that the cumulative distribution $F^{(N)}$ of the supremum of a set of N (equidistributed, unimodal) random variables displays the following universal behaviour as $N \rightarrow \infty$: i) $F^{(N)}$ becomes steeper and steeper, tending to a step-like function, and ii) the CDF inflection point moves forward in x indefinitely. As a result, in the limit $N \rightarrow \infty$, the CDF of the supremum is zero everywhere, except at infinity, where its limiting value is one. EVT is a general framework for dealing with the above limiting process in a meaningful way [30], and relies on a suitable N -dependent change of variable such that the location of the inflection point of $F^{(N)}$ becomes independent of N . It turns out that for most *independent* random variables, it is possible to find two sequences $\{a_N\}$ and $\{b_N > 0\}$ such that

$$\lim_{N \rightarrow \infty} F^{(N)}(a_N + b_N x) \quad (4.24)$$

exists, and can only be one among three *universal* functions: the Frechet, Weibull and Gumbel distributions [30].

Using EVT we can readily prove that as $N \rightarrow \infty$ the cumulative distribution (4.2), converges uniformly to the Gumbel distribution $G^{(N)}(x)$ [31].

In fact, letting $x = y + \log N$ in (4.2) one gets:

$$\Phi_X^{(N)}(y + \log N) = \left(1 - \frac{e^{-y}}{N}\right)^N \xrightarrow{N \rightarrow \infty} e^{-e^{-y}}. \quad (4.25)$$

Switching back to the original variables, one gets:

$$\Phi_X^{(N)}(x) \sim \exp[-N \exp(-x)] = G^{(N)}(x). \quad (4.26)$$

It is also readily proved that the Gumbel distribution $G^{(N)}(x)$ is an *upper bound* for $\Phi_X^{(N)}(x)$, for any N and x , as illustrated in Fig. 2. From the inset in Fig. 2, one can appreciate that $\sup_x [G^{(N)}(x) - \Phi_X^{(N)}(x)]$ drops below 10^{-5} already at $N \sim 10^4$.

For the general realistic case where the covariance among the correlators is nonzero the existence of the a_n and b_n suites in (4.24) is not guaranteed, nor the coincidence with their zero-covariance counterparts is implied. We prove in Appendix A that for *any* nonzero (fixed) template spacing, i.e., for any *nonzero* covariance, $F_X^{(N)}(x)$ converges uniformly to the Gumbel distribution in the limit as $N \rightarrow \infty$, viz.:

$$F_X^{(N)}(y + \log N) \xrightarrow{N \rightarrow \infty} e^{-e^{-y}}. \quad (4.27)$$

The rate of convergence is more or less obviously *slower* the *smaller* the template spacing, i.e., the *larger* the maximum (absolute) covariance. This is illustrated in Fig. 3.

E. Beyond Mohanty-type Formulas

Inspection reveals that the r.h.s.'s of Mohanty-type formulas (4.13), (4.17), (4.23) are bad candidates as CDF approximants. As $x \rightarrow 0+$ they become negative. Even worse, they *do not* exhibit the correct (Gumbel) asymptotic behaviour as $N \rightarrow \infty$. Both these flaws can be remediated by introducing the *exponential* representations [32]

$$\begin{cases} \Psi_{\mathcal{Z}}^{(N_{\Theta})}(x) = \exp[-N_{\Theta}\epsilon(N_{\Theta}, x, \rho_M) \exp(-x)] \\ \Psi_X^{(N)}(x) = \exp[-N_{\Theta}N_{\Delta}\epsilon(N_{\Theta}, x, \rho_M) \exp(-x)] \\ \tilde{\Psi}_X^{(N)}(x) = \exp[-N_{\Theta}N_{\Delta}\epsilon(N_{\Theta}, x, \rho_M)\epsilon(N_{\Delta}, x, \rho'_M) \exp(-x)] \end{cases} \quad (4.28)$$

which are always non negative, have the correct (Gumbel) asymptotic behaviour, and reproduce Mohanty's formulas (4.13), (4.17), (4.23) for x suitably large. We shall prove soon that (4.28) are in turn *lower bounds* for the corresponding exact CDF's. We note from (4.28) that

$$Q_X^{(N)}(x) = \left[Q_X^{(M)}(x)\right]^{N/M}, \quad \forall M < N, \quad N \gg 1, \quad (4.29)$$

where $Q_X^{(N)}$ can be any of the distributions in (4.28).

F. Extrapolating Simulations: A Gaussian Correlation Inequality

The inequality

$$F_X^{(N)}(x) \geq [F_X^{(M)}(x)]^{N/M}, \quad M \leq N \quad (4.30)$$

where $F_X^{(M)}(x)$ is the CDF of the supremum of any *subset* of the whole bank containing $M \leq N$ correlators follows directly from the so called Gaussian Correlation Inequality (henceforth GCI) [33]. More or less obviously, the upper bound in (4.30) is attained as $M \rightarrow N$.

Equation (4.30) is a key to demonstrate that equations in (4.28) are lower bounds for the pertinent *true* cumulative distributions.

As an example, let us consider the case of $\tilde{\Psi}$. Numerical simulations show that for *relatively small* banks,

$$F_X^{(M)}(x) \geq \tilde{\Psi}_X^{(M)}(x). \quad (4.31)$$

On the other hand, in view of eq. (4.29)

$$\left[\tilde{\Psi}_X^{(M)}(x)\right]^{N/M} = \tilde{\Psi}_X^{(N)}(x), \quad N \gg 1, \quad (4.32)$$

and hence, from (4.30),

$$F_X^{(N)}(x) \geq \tilde{\Psi}_X^{(N)}(x), \quad \forall N \gg 1. \quad (4.33)$$

The GCI can be used to extend the validity of *approximate* forms of F_X tested on *relatively small* banks to full-size banks, for which numerical simulations would be impossible or unwieldy.

G. Accuracy and Thresholds

The numerical accuracy of the (lower-bound) approximants (4.28) is illustrated in Figs 4 and 5, obtained from numerical simulations over $\sim 2 \cdot 10^4$ realizations.

Figure 4 refers to the CDF $F_{\mathcal{Z}}^{(N_{\Theta})}$ of a single reduced correlator, and shows that the approximation provided by $\Psi_{\mathcal{Z}}^{(N_{\Theta})}$ is excellent. Figure 5 refers to the CDF of the supremum of a whole bank. For illustrative purposes, we stick at the simplest case of the one-parameter family of (reduced) newtonian waveforms in the range of chirp masses ($0.2M_{\odot} \leq \mathcal{M} \leq 10M_{\odot}$). We assume the (initial) LIGO noise PSD [38],

$$\Pi(f) = \frac{\Pi_0}{5} \left\{ 1 + \left(\frac{f_0}{f}\right)^4 + 2 \left(\frac{f}{f_0}\right)^2 \right\}, \quad (4.34)$$

with $f_0 = 300\text{Hz}$, $f_i = 40\text{Hz}$ and $f_s = 400\text{Hz}$ and Π_0 is a constant of no concern to us here. We sample the data at 3.2KHz (4-times the Nyquist rate), and let $N_\Theta = 2^{21}$, which corresponds to the longest-lived source allowed ($\mathcal{M} = 0.2M_\odot$). Fig. 5 shows that the approximation provided by $\tilde{\Psi}_X^{(N)}$ is fairly good, and notably better than that obtainable from $\Psi_X^{(N)}$. As N (resp. N_Θ) goes to infinity all approximants (4.28) merge by construction into the Gumbel distribution. This latter is indistinguishable from the independent-correlator approximation in both Figs 4 and 5. However, as seen from Figs 4 and 5, in most situations of practical interest for (possibly hierarchical) GW chirp search, eq.s (4.28) would provide significantly better approximants to the relevant CDF's than the plain independent-correlator (or Gumbel) approximation. Being lower bounds, eq.s (4.28) are also conservative in terms of false-alarm probability, when used to set detection thresholds.

A sharper insight into the quality of the various proposed approximants is gained by comparing these latter in terms of the detection threshold corresponding to a given false-alarm probability α , as a function of N_Δ . This is illustrated in Fig. 6, for the special case $\alpha = 10^{-3}$. The thresholds in Fig. 6 correspond to assuming zero covariance among the correlators (dotted line, $\Phi_X^{(N)}$), and to including the covariance among nearest-neighbour correlators along one (coalescence time, dashed line, $\Psi_X^{(N)}$) or both (coalescence time and chirp mass, solid line, $\tilde{\Psi}_X^{(N)}$) coordinates of the newtonian parameter space, respectively.

In Fig. 6, we also include the limiting case where $\Gamma \approx \rho_M \approx 1$. The corresponding (asymptotic) value of γ (dotted-dashed line in Fig. 6) is obtained using the appropriate asymptotic form of $F_X(x)$, first quoted by Krolak [11] after [34] and [35], viz.:

$$F_X(x) \sim 1 - \pi^{-1} \mu[\mathcal{S}'] (\det[\Xi])^{1/2} x \exp(-x), \quad (4.35)$$

where $\mu[\cdot]$ is the Lebesgue measure, $\mathcal{S}'$ is the allowed (reduced) source-parameter space, and Ξ is the covariance matrix of the derivative random-field [36].

V. THE MINIMAL-MATCH ISSUE REVISITED

We are now in a position to re-address the question concerning the relationship between the minimal match Γ (and/or, the number of templates in the parameter-space region of interest) and the undetected fraction of potentially observable sources. For simplicity, we shall again stick at the simplest case of Newtonian waveforms and templates, using the same range of source chirp masses and antenna noise PSD as in Sect. IV G.

It should be noted first that a visible knee point in the Γ vs. N_Δ curve invariably exists at some value $N_\Delta = N_*$, beyond which *any* further increase in N_Δ yields only a *modest* increase in Γ .

This is illustrated in Fig. 7, where a knee point separating intervals of different (almost constant) slope in the Γ versus N_Δ curve occurs at $N_\Delta \approx 5 \cdot 10^3$. Except for the numerical value of N_* , the existence of the above knee point is a *generic* feature of the Γ vs. N_Δ curve, occurring also for more realistic, higher-order post-newtonian waveforms and templates.

Next we focus on eq. (3.8), and use our *best* approximant $\tilde{\Psi}_X^{(N)}(x)$ in eq. (4.28) for the no-signal CDF of the detection statistic in order to compute the ratio $\gamma(\alpha, N_{max})/\gamma(\alpha, N)$ [39]. In Fig. 8 we accordingly compare η_0 (eq. (3.9), dashed line), to η (eq. (3.8), solid lines), for $\alpha = 10^{-k}$, $k = 2, 3, 4$ (top-to bottom), as functions of N_Δ . In Fig. 8 we assumed $\Gamma_{max} = 0.99$ as a *bona fide* practical limiting value, and computed N_{max} accordingly. From Fig. 8 it is seen that a knee point in the curves exists at $N_\Delta \approx N_* \approx 5 \cdot 10^3$. It is also seen that η exceeds by a non negligible 5% typical the plain estimate η_0 discussed in Sect. III, for $N_\Delta \approx N_*$.

It is also interesting to compare in terms of η the alternative approximants for the no-signal CDF of the detection statistic introduced and discussed in Sect. IV. The resulting curves are shown in Fig. 9, where again we assumed $\Gamma_{max} = 0.99$ as a *bona fide* practical limiting value, and computed N_{max} accordingly. The curves in Fig. 9 correspond to assuming zero covariance among the correlators (dotted line, $\Phi_X^{(N)}$), and to including the covariance among nearest-neighbour correlators along one (coalescence time, dashed line, $\Psi_X^{(N)}$) or both (coalescence time and chirp mass, solid line, $\tilde{\Psi}_X^{(N)}$) coordinates of the newtonian parameter space, respectively, in computing $\gamma(\alpha, N_{max})$ in (3.8). For each case, the η vs. N_Δ curves corresponding to $\alpha = 10^{-2}, 10^{-3}, 10^{-4}$ are displayed. It is seen that the dependence of η on α becomes the less relevant, the better approximant is used.

VI. CONCLUSIONS

We presented a detailed analysis of the properties of the cumulative distribution of the whole-bank supremum. A number of tight lower-bound approximations, of increasing accuracy, have been introduced and compared, valid for

any (finite) number of templates. In addition, we studied the asymptotic properties as the number of correlators goes to infinity, in the frame of extremal value theory (EVT). We also shew how the gaussian correlation inequality can be used to extend the validity of simulations made on small-sized (toy) banks.

Concerning the minimal-match issue, we found a consistent evidence that increasing the number of templates beyond a critical value does *not* produce a sensible increase in the detectable fraction of potentially observable sources, at the expense of a marked growth of computational load. On the other hand, using the most accurate representation of the no-signal cumulative distribution of the (whole-bank) detection statistic to compute the threshold results in a sizeable increase in the detectable fraction of potentially observable sources over the naive $\propto \Gamma^3$ estimate.

Acknowledgements

This work has been sponsored in part by the European Community through a Senior Visiting Scientist Grant to I.M. Pinto at NAO - Spacetime Astronomy Division, Tokyo, Japan, in connection with the TAMA project. I.M. Pinto wishes to thank all the TAMA staff at NAO, and in particular prof. Fujimoto Masa-Katsu and prof. Kawamura Seiji for kind hospitality and stimulating discussions.

-
- [1] www.tamago.mtk.nao.ac.jp
 - [2] <http://www.geo600.uni-hannover.de>
 - [3] <http://www.ligo.caltech.edu>
 - [4] <http://www.virgo.infn.it>
 - [5] L.P.Grishchuk, V.M.Lipunov, K.A.Postnov, M.E.Prokhorov, B.S.Sathyaprakash, Phys. Usp. **44** (2001) 1.
 - [6] C. W. Helström, *Statistical Theory of Signal Detection*, Pergamon Press, Oxford (1968).
 - [7] R.P. Croce et al., Class. Quantum Grav., **20**, S803 (2003).
 - [8] R.P. Croce et al., arXiv:gr-qc/0404096 (2004).
 - [9] S.V. Dhurandar, B.F. Schutz, Phys. Rev. **D50** (1994) 2390.
 - [10] S.D. Mohanty and S.V. Dhurandar, Phys. Rev. **D54** (1996) 7108.
 - [11] P. Jaranowski, A. Krolak and B.F. Schutz, Phys. Rev. **D58** (1998) 063001.
 - [12] S.D. Mohanty, Phys. Rev. **D57** (1998) 630.
 - [13] T. Damour, B. R. Iyer, B. S. Sathyaprakash, Phys. Rev. **D62** (2000) 084036.
 - [14] The coalescence time τ is formally defined as the time when the orbital frequency diverges to infinity. The adiabatic inspiral model, however, is only valid up to a last stable circular orbit. See A. Buonanno and T. Damour, Phys. Rev. **D59** (1999) 084006.
 - [15] Th. Apostolatos, Phys. Rev. **D54** (1996) 2421.
 - [16] B. Owen and B. S. Sathyaprakash, Phys. Rev. **D60** (1999) 022002.
 - [17] T. Tanaka and H. Tagoshi, Phys. Rev. **D62** (2000) 082001.
 - [18] R. P. Croce, Th. Demma, V. Pierro, I. M. Pinto, Phys. Rev. **D65** (2002) 102003.
 - [19] The *DFT* definition is here intended to embody the sampling step, so as to make $DFT_n[\cdot] \sim \mathcal{F}_{x \rightarrow f_n}[\cdot]$.
 - [20] In [10] the Authors also restrict to the newtonian case, and consider the one-parameter family of correlators at $\mathcal{M}_T = \mathcal{M}_s$.
 - [21] In [11] the boundary of the correlation neighbourhood of a template is more or less arbitrarily defined as the locus where the overlap equals 1/2.
 - [22] The notable added value of Mohanty's argument is in pointing out that the coefficient ϵ *does depend* on the threshold.
 - [23] The underlying hypothesis is that of a first order Markov process (see e.g., S.O. Rice in N. Wax, *Selected Papers on Noise and Stochastic Processes*, Dover NY, 1966).
 - [24] J. Galambos, I. Simonelli, *Bonferroni-type inequalities with Applications*, Springer, New York NY (1996).
 - [25] A possible exception to this may occur in multi-step hierarchical searches.
 - [26] B. Lévine, *Fondements Théoriques de la Radiotechnique Statistique*, MIR, Moscow, 1973, Vol. 1, Sect. 8.2.2.
 - [27] A.P.Prudnikov, Yu.A. Brychkov, O.I. Marichev, *Integrals and Series*, Gordon and Breach, New York (1992), Vol. II, Sect. 1.2.
 - [28] The r.h.s. of (4.9) turns out to be the *tightest* lower bound expressible in terms of first- and second-order joint probabilities only. See, e.g., [37], th. 1.4.2, where it is shown that suitable selections of higher-order joint-probability terms can be used to construct tighter lower bounds.
 - [29] We note that when the covariance among the correlators is zero,

$$\begin{aligned} \text{Prob}[\mathcal{Z}_{j+1} > x | \mathcal{Z}_j > x, \text{no signal}] &= \text{Prob}[\mathcal{Z}_{j+1} > x | \text{no signal}] \geq \\ &\geq \text{Prob}[\mathcal{Z}_{i,j+1} > x | \text{no signal}] = \text{Prob}[\mathcal{Z}_{i,j+1} > x | \mathcal{Z}_{m,j} > x, \text{no signal}], \end{aligned}$$

and hence (4.21) is verified. On the other hand, in the opposite limiting case where the covariance among the correlators is one, both sides of (4.21) are equal to one and (4.21) still holds.

- [30] E. Castillo, *Extreme Value Theory in Engineering*, Academic Press, London (1988).
- [31] E.J. Gumbel, *Statistics of Extremes*, Columbia Univ. Press, New York NY (1958).
- [32] Recasting the r.h.s. of eq.s (4.13), (4.17) and (4.23) into an *exponential* form bears some similarity to the Rytov technique (see, e.g. L.E. Chernov, *Wave Propagation in a Random Medium*, Dover, New York, NY (1960), p. 58.)
- [33] The GCI involves a gaussian measure μ and a couple of absolutely convex sets A, B , and is

$$\mu(A \cap B) \geq \mu(A)\mu(B).$$

The GCI has been hitherto proved for a wide variety of special meaningful cases (see, e.g., L. Pitt, Ann. Probab. **5**, (1977), 470), and otherwise *never* disproved. As such, it is occasionally quoted as the GCI *conjecture*. An alternative formulation of the GCI is:

$$P\left(\max_{i=1,\dots,N} |X_i| \leq x\right) \geq P\left(\max_{i=1,\dots,M} |X_i| \leq x\right) P\left(\max_{i=M+1,\dots,N} |X_i| \leq x\right)$$

where $\{X_i|i=1,\dots,N\}$ is a set of jointly gaussian r.v. The quoted form follows by induction.

- [34] R.J. Adler and A.M. Hasofer, "Level Crossing for Random Fields," Ann. Prob., **4**, 1-12, 1976.
- [35] K.J. Worsley, Advances in Applied Probability **26** (1994) 13.
- [36] The pertinent derivative random field is more or less obviously $\partial Y/\partial \mathbf{X}$, where $\mathbf{X} = \{\bar{\tau}, \bar{\mathcal{M}}^{-5/3}\}$, $\bar{\tau}$ and $\bar{\mathcal{M}}$ being defined at the beginning of Appendix B, and hence the elements of the covariance matrix $\Xi = E[(\partial Y/\partial \mathbf{X}) \otimes (\partial Y^*/\partial \mathbf{X})]$, are, after some simple calculus,

$$\Xi_{11} = (2\pi)^2 I_1/I_7, \quad \Xi_{12} = \Xi_{21} = 2\pi \lambda I_9/I_7, \quad \Xi_{22} = \lambda^2 I_{17}/I_7$$

where λ is defined in (6.13), I_n are the moments (first introduced by Owen [16])

$$I_n = \int_1^{\bar{f}_s} d\bar{f} \frac{\bar{f}^{-n/3}}{\Pi(\bar{f})},$$

and $\bar{f}$ is defined in Appendix B.

- [37] J. Galambos, *The Asymptotic Theory of Extreme Order Statistics*, John Wiley and Sons, New York, (1984), reprinted by R. Krieger Pub. Co., Malabar FL (1987).
- [38] L. S. Finn and D. Chernoff, Phys. Rev. **D47** (1993) 2198.
- [39] Note that $\gamma(\alpha, N_{max})/\gamma(\alpha, N) \geq 1$, since $\gamma(\alpha, N)$ is a non-decreasing function of N , whatever α .
- [40] L. Pitt, Ann. Probab., **5**, 470 (1977).
- [41] V.I. Bogachev, *Gaussian Measures*, Mathematical Surveys and Monographs, American Mathematical Society, Providence RH (1998), vol. 62, Sect. 4.6).
- [42] A *standard* centered gaussian measure can be obtained from a *general* centered gaussian measure by mean of a linear (invertible) transformation, which obviously preserves the properties of the sets $\mathcal{A}$ and $\mathcal{D}$.
- [43] The chirp-mass is $\mathcal{M} = \mu^{3/5} M_{tot}^{2/5}$, where μ and M_{tot} are the reduced and total mass of the source, respectively.
- [44] The relevant large asymptotic parameter is the ratio $cT_0/\pi r_g$, where T_0 and r_g are the source (initial) orbital period and gravitational radius.
- [45] These are related to the weak mixing conditions D and D' quoted in Castillo's book [30].
- [46] V.I. Arnold, A. Avez, *Problèmes Ergodiques del la Mécanique Classique*, Gauthier-Villars, Paris, (1967).
- [47] The required stationarity here refers to the joint CDFs, and is implied for gaussian correlators by the stationarity of the correlation matrix .
- [48] M. Abramowitz, I.A. Stegun, *Handbook of Mathematical Functions*, Dover Publ., New York (1970).
- [49] One could readily prove that also the supremum of the whole-bank subsets corresponding to a fixed coalescency time belongs asymptotically to the Gumbel universal class, as the pertinent number of correlators N_Δ goes to infinity. To this end, it is sufficient to rephrase Lemma **B.2** by noting that

$$\tilde{\rho}_m = o\left(\frac{1}{m}\right),$$

where

$$\tilde{\rho}_{m+1} = |E[Y_{j,k} Y_{j,k+m}^*]|, \tag{6.1}$$

which follows from the asymptotic (stationary phase) evaluation for $\Delta \longrightarrow \infty$ of the integral :

$$\rho(0, \Delta) = \left| \frac{1}{\mathcal{N}} \int_1^{\bar{f}_s} \frac{\bar{f}^{-7/3}}{\Pi(\bar{f})} \exp[j(\lambda \bar{f}^{-5/3} \Delta)] d\bar{f} \right| = o\left(\frac{1}{\Delta}\right).$$

Rephrasing the subsequent Lemmas **B.3** to **B.6** as well as Theorem 1 is straightforward.

- [50] A.N. Shirayev, *Probability*, Springer-Verlag, New York NY (1984).

Appendix A - Proof of Equation (4.3)

In this appendix we prove that the CDF of the whole-bank supremum for the independent-correlator case is a lower bound for the true one. The proof relies on two preliminary Lemmas.

Lemma A.1 (Pitt's theorem [40]) - Let μ a centered gaussian measure [41] in $\mathbf{C}$, and let $\mathcal{A}, \mathcal{B}$ two centered convex symmetric sets in $\mathbf{C}$. Then

$$\mu(\mathcal{A} \cap \mathcal{B}) \geq \mu(\mathcal{A}) \mu(\mathcal{B}). \quad (6.2)$$

Remark - Pitt's theorem can be rephrased in functional (integral) form as

$$E(fg) \geq E(f)E(g), \quad (6.3)$$

where f, g are log-concave symmetric functions and $E(\cdot)$ is e.g. the mean value w.r.t. to a centered complex gaussian measure μ .

The following Lemma is a more or less obvious extension of the above to $\mathbf{C}^N$.

Lemma A.2 Let μ_N a centered gaussian measure in $\mathbf{C}^N$. For any convex symmetric set $\mathcal{A} \in \mathbf{C}^N$, and any $\mathcal{D} = \{\vec{x} \in \mathbf{C}^N : |f(\vec{x})| \leq r\}$, where f is any linear functional in $\mathbf{C}^N$ and $r \in \mathbf{R}$, one has

$$\mu_N(\mathcal{A} \cap \mathcal{D}) \geq \mu_N(\mathcal{A})\mu_N(\mathcal{D}). \quad (6.4)$$

Proof - It suffices to prove the Lemma assuming that μ_N is a *standard* gaussian measure [42].

Under a suitable unitary transformation (preserving obviously the gaussian character of the measure μ_N) the set $\mathcal{D}$ can be transformed into:

$$\mathcal{D} = \{\vec{y} \in \mathbf{C}^N : |y_1| \leq r\}. \quad (6.5)$$

Now let

$$\psi(z) = \int_{\mathbf{C}^{N-1}} I_{\mathcal{A}}(z, \vec{v}) \mu_{N-1}(d\vec{v}), \quad (6.6)$$

where $I_{\mathcal{A}}(z, \vec{v})$ denotes the indicator of $\mathcal{A}$, $z \in \mathbf{C}$ and $\vec{v} \in \mathbf{C}^{N-1}$. $I_{\mathcal{A}}(z, \vec{v})$ is a non negative log-concave function, and μ_{N-1} is a non negative log-concave measure, whose related PDF is also non negative and log-concave. Thus, according to theorem 4.6 in Bogachev [41], $\psi(z)$ is non negative and log-concave. The symmetry properties of $\mathcal{A}$ and μ_{N-1} imply that $\psi(z)$ is an even function. The level-sets $\psi(z) > r$ are thus convex and symmetric.

Hence, letting $\mathcal{U} = \{z \in \mathbf{C}, |z| \leq r\}$, by eq. (6.3):

$$\int_{\mathbf{C}} \psi(z) I_{\mathcal{U}}(z) \mu_1(dz) \geq \int_{\mathbf{C}} \psi(z) \mu_1(dz) \int_{\mathbf{C}} I_{\mathcal{U}}(z) \mu_1(dz) = \mu_N(\mathcal{A}) \mu_N(\mathcal{D}). \quad (6.7)$$

On the other hand one has trivially:

$$\begin{aligned} \int_{\mathbf{C}} \psi(z) I_{\mathcal{U}}(z) \mu_1(dz) &= \int_{\mathbf{C}^N} I_{\mathcal{A}}(z, \vec{v}) I_{\mathcal{U}}(z) \mu_N(dz \times d\vec{v}) = \\ &= \int_{\mathbf{C}^N} I_{\mathcal{A} \cap \mathcal{D}}(z, \vec{v}) \mu_N(dz \times d\vec{v}) = \mu_N(\mathcal{A} \cap \mathcal{D}). \end{aligned} \quad (6.8)$$

Statement (6.4) follows from (6.7) and (6.8) •

We are now in a position to provide the

Proof of Eq. (4.3) - Equation (4.3) in Sect. IV can be rephrased as

$$\text{Prob}(|Y_1| \leq y_1, \dots, |Y_N| \leq y_N) \geq \prod_{i=1}^N \text{Prob}(|Y_i| \leq y_i), \quad (6.9)$$

where Y_i , $i = 1, 2, \dots, N$ are centered jointly gaussian random variables in $\mathbf{C}^N$. Let μ_N a centered gaussian measure in $\mathbf{C}^N$, and define the (*convex, symmetric*) sets:

$$\mathcal{A}_i = \{\vec{a} \in \mathbf{C}^N : |a_i| \leq y_i\}. \quad (6.10)$$

Inequality (6.9) can be rewritten:

$$\mu_N \left(\bigcap_{i=1}^N \mathcal{A}_i \right) \geq \prod_{i=1}^N \mu_N(\mathcal{A}_i), \quad (6.11)$$

which follows by induction from Lemma A.2 •

Appendix B - Asymptotic Properties of Bank Supremums CDF

In this appendix we prove that the CDF of the supremum of the bank correlator subsets corresponding to a fixed chirp mass, as well as the CDF of the supremum of the whole bank belong asymptotically to the Gumbel universal class, as the pertinent number of correlators goes to infinity (theorem 1 and 2, respectively).

Throughout this Appendix we shall restrict to the simplest case of newtonian (0PN) waveforms and templates, for which

$$\psi_T(f, \vec{\xi}_T) = \frac{3}{128} \left(\frac{\pi G}{c^3} \right)^{-5/3} \mathcal{M}_T^{-5/3} f^{-5/3} \quad (6.12)$$

where $\mathcal{M}_T$ is the template chirp mass [43] and c , G have obvious meanings.

It is convenient to introduce the following dimensionless variables and parameters:

$$\bar{f} = \frac{f}{f_i}, \quad \bar{\tau} = f_i \tau, \quad \bar{\mathcal{M}} = \frac{\mathcal{M}}{M_\odot}, \quad \lambda = \frac{3}{128} \left(\frac{\pi G f_i M_\odot}{c^3} \right)^{-5/3}, \quad (6.13)$$

where $M_\odot$ is the solar mass.

The complex random field (2.23) and the pertinent *absolute* covariance (2.27) in turn become:

$$Y(\tau_T, \xi_T) = Y(\bar{\tau}, \bar{\mathcal{M}}) \quad (6.14)$$

and

$$|E[Y(\bar{\tau}, \bar{\mathcal{M}})Y^*(\bar{\tau}', \bar{\mathcal{M}}')]| = \frac{\left| \int_1^{\bar{f}_s} \bar{f}^{-7/3} \exp \left\{ j \left[2\pi \bar{f} \Theta + \lambda \Delta \bar{f}^{-5/3} \right] \right\} \frac{d\bar{f}}{\Pi(\bar{f})} \right|}{\left| \int_1^{\bar{f}_s} \bar{f}^{-7/3} \frac{d\bar{f}}{\Pi(\bar{f})} \right|} =: \rho(\Theta, \Delta) \quad (6.15)$$

where $\Theta = \bar{\tau}' - \bar{\tau}$ and $\Delta = \bar{\mathcal{M}}'^{-5/3} - \bar{\mathcal{M}}^{-5/3}$.

Specializing eq. (2.31) to the newtonian case, according to (6.14) and (6.15), we introduce the 2D stationary sequence

$$Y_{h,k} = Y(h\delta_\Theta, k\delta_\Delta), \quad h, k \in \mathbf{N}, \quad (6.16)$$

and further define:

$$\rho_{m+1} = \rho(m\delta_\Theta, 0), \quad (6.17)$$

$$\bar{\rho}_{m+1} = \max_{h=1, \dots, N_\Theta} \rho(h\delta_\Theta, m\delta_\Delta), \quad (6.18)$$

δ_Θ and δ_Δ being the discretization steps in $\bar{\tau}$ and $\bar{\mathcal{M}}$, respectively.

We start by proving the following Lemma:

Lemma B.1 - If the equation

$$\Pi(\bar{f}) + 2\bar{f}\Pi'(\bar{f}) = 0, \quad (6.19)$$

has at least one solution $\bar{f} \in [1, \bar{f}_s]$, where $\Pi(\bar{f})$ is the antenna noise power spectral density, then

$$\bar{\rho}_m = o\left(\frac{1}{\sqrt{m}}\right). \quad (6.20)$$

Otherwise,

$$\bar{\rho}_m = o\left(\frac{1}{m}\right). \quad (6.21)$$

Proof - Note first that:

$$\bar{\rho}_m \leq \max_{\Theta} \rho(\Theta, \Delta) = \rho[\Theta_{max}(\Delta), \Delta], \quad (6.22)$$

where Θ on the r.h.s. is a continuous variable, and $\Theta_{max}(\Delta)$ is the solution (in Θ) of:

$$\frac{\partial \rho(\Theta, \Delta)}{\partial \Theta} = 0. \quad (6.23)$$

The proof for the special case where (6.19) has no root in $[1, \bar{f}_s]$ follows immediately by Lebesgue theorem (integration by parts).

The proof for the special case where (6.19) has (at least) one root in $[1, \bar{f}_s]$ is readily obtained using the asymptotic stationary phase formula [44] to compute the correlator (2.1). The phase stationary point in (2.1) is:

$$\bar{f} = \frac{5^{3/8}}{8\pi} \left(\frac{c^3}{GM_\odot} \right)^{5/8} \left(\frac{\Delta}{\Theta} \right)^{3/8} = \bar{f}_a \quad (6.24)$$

and the (absolute) correlation function can be accordingly written:

$$\rho(\Theta, \Delta) \sim 4\pi^{4/3} \sqrt{\frac{6}{5}} \left(\frac{GM_\odot}{c^3} \right)^{5/6} \Delta^{-1/2} \frac{\bar{f}_a^{-1/2}}{\Pi(\bar{f}_a)}, \quad (6.25)$$

where $\bar{f}_a$ depends on Θ (and Δ) through eq. (6.24). It is readily checked that $\partial \bar{f}_a / \partial \Theta$ is always nonzero, so that the solution of (6.23) are those of:

$$\frac{\partial \rho(\Theta, \Delta)}{\partial \bar{f}_a} = 0, \quad (6.26)$$

which is nothing but eq. (6.19), whose assumedly existing solution will be denoted as $\bar{f}_a^\dagger$. Hence

$$\max_{\Theta} \rho(\Theta, \Delta) \sim 4\pi^{4/3} \sqrt{\frac{6}{5}} \left(\frac{GM_\odot}{c^3} \right)^{5/6} \Delta^{-1/2} \frac{\bar{f}_a^{\dagger-1/2}}{\Pi(\bar{f}_a^\dagger)}. \quad (6.27)$$

The statement follows from (6.27) together with (6.22) •

Remark - For *all* first generation interferometers equation (6.19) has just one solution $\bar{f}_a^\dagger \in [1, \bar{f}_s]$. Note that $\bar{f}_a^\dagger$ does *not* depend on Δ .

Lemma B.2 - The following statement is true:

$$\rho_m = o\left(\frac{1}{m}\right). \quad (6.28)$$

Proof - The Lemma is based on the (stationary phase) asymptotic evaluation for $\Theta \rightarrow \infty$ of the integral:

$$\rho(\Theta, 0) = \left| \frac{1}{\mathcal{N}} \int_1^{\bar{f}_s} \frac{\bar{f}^{-7/3}}{\Pi(\bar{f})} \exp[j2\pi\bar{f}\Theta] d\bar{f} \right| = o\left(\frac{1}{\Theta}\right) \bullet \quad (6.29)$$

We shall now introduce two ancillary conditions, which are suitable weak (asymptotic) versions of the M -dependence condition [45]. In particular condition #1 is similar to the mixing condition of dynamical systems [46].

Condition 1 - Let $\{X_j\}$ a sequence of random variables, and let $F_{j_1, j_2, \dots, j_r}(x_1, x_2, \dots, x_r)$ the joint CDF of $X_{j_1}, X_{j_2}, \dots, X_{j_r}$. Condition #1 holds if, for any set of integers $\{i_1 < i_2, \dots < i_p\}$ and $\{j_1 < j_2, \dots < j_q\}$ such that $j_1 - i_p \geq s$, and any real number u , a real-valued function $g(s)$ exists such that:

$$\left| F_{X_{i_1}, \dots, X_{i_p}, X_{j_1}, \dots, X_{j_q}}(u, u, \dots, u) - F_{X_{i_1}, \dots, X_{i_p}}(u, u, \dots, u) F_{X_{j_1}, \dots, X_{j_q}}(u, u, \dots, u) \right| \leq g(s), \quad (6.30)$$

with

$$\lim_{s \rightarrow \infty} g(s) = 0. \quad (6.31)$$

Condition 2: Let $\{u_n\}$ a sequence of reals, and let $\{X_j\}$ a stationary [47] random sequence. Condition #2 holds if:

$$\lim_{k \rightarrow \infty} \limsup_{n \rightarrow \infty} \left\{ n \sum_{j=2}^{\lfloor n/k \rfloor} \text{Prob}[X_1 > u_n, X_j > u_n] \right\} = 0. \quad (6.32)$$

Conditions #1 and #2 above imply the following

Lemma B.3 ([30], theorem 8.5) Let $\{X_j\}$ a stationary sequence of random variables and let $\{a_n\}, \{b_n\}$ two sequences of reals. Assume that conditions #1 and #2 are satisfied with $u_n = a_n + b_n x$. Let $\{X'_j\}$ a sequence of i.i.d. random

variables having the same CDF as $\{X_j\}$, and $\mathcal{G}(x)$ any of the (three) universal extremal limit distributions [37] of i.i.d. random variables. Then:

$$\lim_{n \rightarrow \infty} \text{Prob} \left[\max_{j=1, \dots, n} X_j \leq a_n + b_n x \right] = \mathcal{G}(x) \quad (6.33)$$

and

$$\lim_{n \rightarrow \infty} \text{Prob} \left[\max_{j=1, \dots, n} X'_j \leq a_n + b_n x \right] = \mathcal{G}(x) \quad (6.34)$$

are equivalent.

Lemma **B.3** plays a key role. Loosely speaking, it states that provided conditions #1 and #2 are satisfied, the supremum of a (stationary, *dependent*) sequence has the same CDF as if the sequence was made of independent r.v.

We are now in a position to prove three key Lemmas.

Lemma B.4 - Let $G_i = Y_{i,k}$ with $k \in \mathbf{N}$ fixed, and let $Z_i = |G_i|^2$. The Z_i satisfy condition #1.

Proof - Let $\{i_1 < i_2, \dots < i_p\}$ and $\{j_1 < j_2, \dots < j_q\}$ two set of integers such that $j_1 - i_p \geq s$. Let further $\mathbf{C}_p$ and $\mathbf{C}_q$ and $\mathbf{C}_{p+q}$ the correlation matrices of the zero-average complex gaussian random sequences $\{G_{i_1}, \dots, G_{i_p}\}$, $\{G_{j_1}, \dots, G_{j_q}\}$, and $\{G_{i_1}, \dots, G_{i_p}, G_{j_1}, \dots, G_{j_q}\}$, respectively. Let $\mathbf{C}_1 = \mathbf{C}_{p+q}$ and $\mathbf{C}_2 = \text{diag}[\mathbf{C}_p, \mathbf{C}_q]$, and $\mathbf{G} = [G_{i_1}, \dots, G_{i_p}, G_{j_1}, \dots, G_{j_q}]$, and let

$$F_{Z_{i_1}, \dots, Z_{i_p}, Z_{j_1}, \dots, Z_{j_q}}(u, u, \dots, u) = \frac{\omega}{\det^{p+q} \mathbf{C}_1} \int_{\mathcal{E}} e^{-\mathbf{G}^* \mathbf{C}_1^{-1} \mathbf{G}} d^{p+q} \mathbf{G} \quad (6.35)$$

and

$$F_{Z_{i_1}, \dots, Z_{i_p}}(u, u, \dots, u) F_{Z_{j_1}, \dots, Z_{j_q}}(u, u, \dots, u) = \frac{\omega}{\det^{p+q} \mathbf{C}_2} \int_{\mathcal{E}} e^{-\mathbf{G}^* \mathbf{C}_2^{-1} \mathbf{G}} d^{p+q} \mathbf{G} \quad (6.36)$$

the pertinent cumulative distributions, ω being a suitable normalization constant, and $\mathcal{E}$ the domain $(|G_i| \leq \sqrt{u} \cap |G_j| \leq \sqrt{u})$.

The Z_i satisfy condition #1 iff:

$$\lim_{s \rightarrow \infty} \left| \frac{1}{\det^{p+q} \mathbf{C}_1} \int_{\mathcal{E}} e^{-\mathbf{G}^* \mathbf{C}_1^{-1} \mathbf{G}} d^{p+q} \mathbf{G} - \frac{1}{\det^{p+q} \mathbf{C}_2} \int_{\mathcal{E}} e^{-\mathbf{G}^* \mathbf{C}_2^{-1} \mathbf{G}} d^{p+q} \mathbf{G} \right| = 0. \quad (6.37)$$

Under the assumption

$$\lim_{m \rightarrow \infty} E[G_i G_{i+m}^*] = \lim_{m \rightarrow \infty} E[Y_{i,k} Y_{i+m,k}^*] = \lim_{m \rightarrow \infty} \rho_{m+1} = 0, \quad \forall i,$$

which holds in view of Lemma **B.2**, the off-diagonal blocks in $\mathbf{C}_1$ go to zero, and hence

$$\lim_{s \rightarrow \infty} (\mathbf{C}_1 - \mathbf{C}_2) = 0 \implies \lim_{s \rightarrow \infty} (\det \mathbf{C}_1 - \det \mathbf{C}_2) = 0. \quad (6.38)$$

To prove (6.37) we note that:

$$\left| \frac{1}{\det^{p+q} \mathbf{C}_1} e^{-\mathbf{G}^* \mathbf{C}_1^{-1} \mathbf{G}} - \frac{1}{\det^{p+q} \mathbf{C}_2} e^{-\mathbf{G}^* \mathbf{C}_2^{-1} \mathbf{G}} \right| \leq$$

$$\begin{aligned}
&= \frac{e^{-\mathbf{G}^* \mathbf{C}_1^{-1} \mathbf{G}}}{\det^{p+q} \mathbf{C}_1} \left[1 - e^{-\mathbf{G}^* (\mathbf{C}_2^{-1} - \mathbf{C}_1^{-1}) \mathbf{G}} \right] + \frac{e^{-\mathbf{G}^* \mathbf{C}_2^{-1} \mathbf{G}}}{\det^{p+q} \mathbf{C}_1} \left| 1 - \left(\frac{\det \mathbf{C}_1}{\det \mathbf{C}_2} \right)^{p+q} \right| \leq \\
&\leq \frac{e^{-\mathbf{G}^* \mathbf{C}_1^{-1} \mathbf{G}}}{\det^{p+q} \mathbf{C}_1} \left[e^{|\mathbf{G}|^2 \|\mathbf{C}_2^{-1} - \mathbf{C}_1^{-1}\|} - 1 \right] + \frac{e^{-\mathbf{G}^* \mathbf{C}_2^{-1} \mathbf{G}}}{\det^{p+q} \mathbf{C}_1} \left| 1 - \left(\frac{\det \mathbf{C}_1}{\det \mathbf{C}_2} \right)^{p+q} \right|, \tag{6.39}
\end{aligned}$$

where $\|\cdot\|$ is the (matrix) L_2 norm. Using further the simple inequality $|\mathbf{G}|^2 \leq \sum_{h=1}^p |G_{ih}|^2 + \sum_{k=1}^q |G_{jk}|^2 \leq (p+q)u$, we obtain from (6.39):

$$\begin{aligned}
&\left| \frac{1}{\det^{p+q} \mathbf{C}_1} e^{-\mathbf{G}^* \mathbf{C}_1^{-1} \mathbf{G}} - \frac{1}{\det^{p+q} \mathbf{C}_2} e^{-\mathbf{G}^* \mathbf{C}_2^{-1} \mathbf{G}} \right| \leq \\
&\leq \frac{1}{\det^{p+q} \mathbf{C}_1} \left\{ \left[e^{(p+q)u \|\mathbf{C}_2^{-1} - \mathbf{C}_1^{-1}\|} - 1 \right] + \left| 1 - \left(\frac{\det \mathbf{C}_1}{\det \mathbf{C}_2} \right)^{p+q} \right| \right\} \Rightarrow_{s \rightarrow \infty} 0, \tag{6.40}
\end{aligned}$$

in view of (6.38). Equation (6.37) follows •

The next Lemma **B.5** is needed to prove Lemma **B.6**.

Lemma B.5 - Let G_1 and G_2 two complex standard gaussian random variables, and let:

$$c = |E[G_1 G_2^*]| < 1. \tag{6.41}$$

The following inequality holds:

$$\text{Prob} [|G_1|^2 > u, |G_2|^2 > u] \leq \frac{1+c}{1-c} e^{-\frac{2}{1+c}u}. \tag{6.42}$$

Proof - From the standard definition of bivariate (complex) normal variables,

$$\text{Prob} [|G_1|^2 > u, |G_2|^2 > u] = \frac{4}{1-c^2} \int_{\sqrt{u}}^{\infty} \int_{\sqrt{u}}^{\infty} x_1 x_2 e^{-\frac{x_1^2 + x_2^2}{1-c^2}} I_0 \left(\frac{2c}{1-c^2} x_1 x_2 \right) dx_1 dx_2, \tag{6.43}$$

where $I_0(\cdot)$ is the modified Bessel function. Representing this latter in integral form [48], gives:

$$\text{Prob} [|G_1|^2 > u, |G_2|^2 > u] \leq \frac{4}{1-c^2} \int_{\sqrt{u}}^{\infty} \int_{\sqrt{u}}^{\infty} x_1 x_2 e^{-\frac{x_1^2 + x_2^2 - 2cx_1 x_2}{1-c^2}} dx_1 dx_2. \tag{6.44}$$

Switching to polar coordinates (ρ, ϕ) ,

$$x_1^2 + x_2^2 - 2cx_1 x_2 = \rho^2(1 - c \sin 2\phi) \geq \rho^2(1 - c), \tag{6.45}$$

whence:

$$\begin{aligned}
&\text{Prob} [|G_1|^2 > u, |G_2|^2 > u] \leq \frac{4}{1-c^2} \int_{\sqrt{u}}^{\infty} \int_{\sqrt{u}}^{\infty} x_1 x_2 e^{-\frac{x_1^2 + x_2^2}{1-c^2}(1-c)} dx_1 dx_2 = \\
&= \frac{4}{1-c^2} \int_{\sqrt{u}}^{\infty} \int_{\sqrt{u}}^{\infty} x_1 x_2 e^{-\frac{x_1^2 + x_2^2}{1+c}} dx_1 dx_2 = \frac{4}{1-c^2} \left[\int_{\sqrt{u}}^{\infty} x_1 e^{-\frac{x_1^2}{1+c}} dx_1 \right]^2 = \frac{1+c}{1-c} e^{-2\frac{u}{1+c}}, \tag{6.46}
\end{aligned}$$

q.e.d. •

Lemma B.6 - Let $\{H_j\}$ a sequence of complex standard gaussian random variables, let $u_n = \log n + x$, and let:

$$\gamma_{m+1} = |E [H_1 H_{1+m}^*]| < 1, \quad m \neq 0. \quad (6.47)$$

If, for some $0 < \beta < \infty$

$$\gamma_m = o\left(\frac{1}{m^\beta}\right), \quad (6.48)$$

then:

$$\lim_{k \rightarrow \infty} \limsup_{n \rightarrow \infty} \left\{ n \sum_{j=2}^{\lfloor n/k \rfloor} \text{Prob} \left[|H_1|^2 > u_n, |H_j|^2 > u_n \right] \right\} = 0. \quad (6.49)$$

Proof - In view of Lemma B.5,

$$S_n = n \sum_{j=2}^{\lfloor n/k \rfloor} \text{Prob} \left[|H_1|^2 > \log n + x, |H_j|^2 > \log n + x \right] \leq nM \sum_{j=2}^{\lfloor n/k \rfloor} e^{-\frac{2}{\gamma_j+1} \log n} = M \sum_{j=2}^{\lfloor n/k \rfloor} n^{\frac{\gamma_j-1}{\gamma_j+1}}, \quad (6.50)$$

where:

$$M = \frac{1+\bar{\gamma}}{1-\bar{\gamma}} e^{2|x|}, \quad \bar{\gamma} = \sup_{j \geq 2} \gamma_j < 1. \quad (6.51)$$

The last inequality follows from $\gamma_j < 1 \quad \forall j \geq 2$, and from the asymptotic decay rate of γ_j .
From eq.(6.50) one readily gets:

$$S_n \leq M \sum_{j=2}^{\lfloor n/k \rfloor} \lfloor n/k \rfloor^{\frac{\gamma_j-1}{\gamma_j+1}} k^{\frac{\gamma_j-1}{\gamma_j+1}}. \quad (6.52)$$

Letting in (6.52) $m = \lfloor n/k \rfloor$, and using the obvious inequality:

$$k^{\frac{\gamma_j-1}{\gamma_j+1}} \leq m^{\frac{\bar{\gamma}-1}{\bar{\gamma}+1}} \quad \forall j \geq 2, \quad (6.53)$$

eq. (6.50) becomes:

$$S_n \leq M m^{\frac{\bar{\gamma}-1}{\bar{\gamma}+1}} \sum_{j=2}^m m^{\frac{\gamma_j-1}{\gamma_j+1}}. \quad (6.54)$$

The Lemma now readily follows from the fact that:

$$\lim_{m \rightarrow \infty} \sum_{j=2}^m m^{\frac{\gamma_j-1}{\gamma_j+1}} = 1. \quad (6.55)$$

Indeed letting:

$$\bar{S}_m = \sum_{j=2}^m m^{\frac{\gamma_j-1}{\gamma_j+1}} - 1 = \sum_{j=2}^m \left(m^{\frac{\gamma_j-1}{\gamma_j+1}} - \frac{1}{m} \right) - \frac{1}{m}, \quad (6.56)$$

and taking limit $m \rightarrow \infty$, one gets:

$$\bar{S}_m \sim \sum_{j=2}^m \left(m^{\frac{\gamma_j-1}{\gamma_j+1}} - \frac{1}{m} \right) = \sum_{j=2}^m \frac{e^{\frac{2\gamma_j}{\gamma_j+1} \log m} - 1}{m}. \quad (6.57)$$

Obviously,

$$\forall \delta > 1, \quad \exists \zeta_0 : e^\zeta - 1 < \delta \zeta, \quad \forall \zeta \in [0, \zeta_0]. \quad (6.58)$$

Now let j' the *smallest* integer such that:

$$\frac{2\gamma_j}{1+\gamma_j} \log m \leq \zeta_0 \quad \forall j \geq j'. \quad (6.59)$$

Then:

$$\frac{2\gamma_{j'-1}}{\gamma_{j'-1}+1} \log m > \zeta_0, \quad (6.60)$$

and

$$e^{\frac{2\gamma_j}{\gamma_j+1} \log m} - 1 < \frac{2\delta\gamma_j}{1+\gamma_j} \log m, \quad \forall j \geq j'. \quad (6.61)$$

Let:

$$\bar{S}_m \sim \sum_{j=2}^{j'-1} \frac{e^{\frac{2\gamma_j}{\gamma_j+1} \log m} - 1}{m} + \sum_{j=j'}^m \frac{e^{\frac{2\gamma_j}{\gamma_j+1} \log m} - 1}{m}. \quad (6.62)$$

We can use the inequality (6.61) to show that the second partial sum in (6.62) vanishes in the limit $m \rightarrow \infty$. Indeed:

$$\begin{aligned} \sum_{j=j'}^m \frac{e^{\frac{2\gamma_j}{\gamma_j+1} \log m} - 1}{m} &\leq \frac{2\delta \log m}{m} \sum_{j=j'}^m \frac{\gamma_j}{1+\gamma_j} \leq \frac{2\delta \log m}{m} \max_{j=j', \dots, m} (\gamma_j j^\beta) \sum_{j=j'}^m j^{-\beta} \\ &\leq \frac{2\delta \log m}{m} \max_{j=j', \dots, m} (\gamma_j j^\beta) \int_1^m j^{-\beta} dj = \frac{2\delta \log m}{m} \max_{j=j', \dots, m} (\gamma_j j^\beta) \left(\frac{m^{1-\beta} - 1}{1-\beta} \right). \end{aligned} \quad (6.63)$$

On the other hand in view of (6.51):

$$\sum_{j=2}^{j'-1} \frac{e^{\frac{2\gamma_j}{\gamma_j+1} \log m} - 1}{m} \leq (j'-2) \frac{e^{\frac{2\gamma_{j'-1}}{\gamma_{j'-1}+1} \log m} - 1}{m} = \frac{(j'-2)(\gamma_{j'-1})^{1/\beta}}{(\gamma_{j'-1})^{1/\beta}} \left(m^{\frac{\bar{\gamma}-1}{\bar{\gamma}+1}} - \frac{1}{m} \right).$$

Now we can use the inequality (6.60) to show that the first partial sum in (6.62) also vanishes in the limit $m \rightarrow \infty$:

$$\sum_{j=2}^{j'-1} \frac{e^{\frac{2\gamma_j}{\gamma_j+1} \log m} - 1}{m} \leq (j'-2)(\gamma_{j'-1})^{1/\beta} \left(\frac{2 \log m}{\zeta_0} - 1 \right)^{1/\beta} \left(m^{\frac{\bar{\gamma}-1}{\bar{\gamma}+1}} - \frac{1}{m} \right). \quad (6.64)$$

This completes the proof •

Remark - Lemma **B.6** holds for general (i.e., stationary as well as non-stationary) sequences. This most general case will be invoked in Lemma **B.8**.

From Lemmas **B.3** to **B.6**, one readily proves that the CDF of the supremum of the whole-bank subsets corresponding to a fixed chirp mass belongs asymptotically to the Gumbel universal class, as the pertinent number of correlators N_Θ goes to infinity [49].

Theorem 1 - Let $Z_j = |Y_{j,k}|^2$, $k \in \mathbf{N}$ being fixed. If, for some $0 < \beta < \infty$

$$\rho_m = o\left(\frac{1}{m^\beta}\right), \quad (6.65)$$

then the supremum of $\{Z_j | j = 1, \dots, N_\Theta\}$ is asymptotically Gumbel-distributed for $N_\Theta \rightarrow \infty$, viz.:

$$\lim_{N_\Theta \rightarrow \infty} \text{Prob} \left[\max_{j=1, \dots, N_\Theta} Z_j \leq \log N_\Theta + x \right] = \exp[-\exp(-x)], \quad \forall k. \quad (6.66)$$

Proof - The Z_j are exponentially distributed. If they were independent, eq. (6.66) would be trivial, as noted in Sect. IV. However, $\forall k \in \mathbf{N}$, the sequence Z_j satisfies both conditions #1 and #2, with $u_n = \log n + x$, in view of Lemmas B.4 and B.6. Thus by Lemma B.3, eq. (6.66) holds true despite the Z_j being dependent •

We turn now to prove Theorem 2. To this end we start with two relevant Lemmas.

Lemma B.7 - Let:

$$\mathcal{Z}_k = \max_{j=1, \dots, N_\Theta} |Y_{j,k}|^2. \quad (6.67)$$

The sequence $\{\mathcal{Z}_k\}$ satisfies condition #1.

Proof - From the obvious relation

$$\text{Prob}[\mathcal{Z}_k \leq u] = \text{Prob}[|Y_{1,k}|^2 \leq u, |Y_{2,k}|^2 \leq u, \dots, |Y_{N_\Theta,k}|^2 \leq u], \quad (6.68)$$

the probability $\text{Prob}[\mathcal{Z}_k \leq u]$ is a joint probability of gaussian complex variables. The proof follows from Lemma B.4 •

Lemma B.8 - If, for some $0 < \bar{\beta} < \infty$

$$\bar{\rho}_m = o\left(\frac{1}{m^{\bar{\beta}}}\right), \quad (6.69)$$

then the sequence $\{\mathcal{Z}_k\}$ satisfies condition #2, with $u_n = \log n + x$.

Proof - Let

$$E_h = \begin{cases} \text{True}, \mathcal{Z}_h > u_n \\ \text{False}, \mathcal{Z}_h \leq u_n \end{cases}, \quad h = 1, \dots, N_\Delta, \quad (6.70)$$

and let

$$E_{j,h} = \begin{cases} \text{True}, |Y_{j,h}|^2 > u_n \\ \text{False}, |Y_{j,h}|^2 \leq u_n \end{cases}, \quad j = 1, \dots, N_\Theta \quad h = 1, \dots, N_\Delta. \quad (6.71)$$

Clearly $E_h = \bigcup_{j=1}^{N_\Theta} E_{j,h}$, and hence:

$$\text{Prob}[E_1 \cap E_k] = \text{Prob} \left[\left(\bigcup_{i=1}^{N_\Theta} E_{i,1} \right) \cap \left(\bigcup_{j=1}^{N_\Theta} E_{j,k} \right) \right] = \text{Prob} \left[\bigcup_{i,j=1}^{N_\Theta} (E_{i,1} \cap E_{j,k}) \right] \leq \sum_{i,j=1}^{N_\Theta} \text{Prob}[E_{i,1} \cap E_{j,k}]. \quad (6.72)$$

Now condition #2 for $\mathcal{Z}_k$ can be written:

$$\lim_{m \rightarrow \infty} \limsup_{n \rightarrow \infty} \left\{ n \sum_{k=2}^{\lfloor n/m \rfloor} \text{Prob}[\mathcal{Z}_1 > u_n, \mathcal{Z}_k > u_n] \right\} = 0. \quad (6.73)$$

On the other hand,

$$\lim_{m \rightarrow \infty} \limsup_{n \rightarrow \infty} \left\{ n \sum_{k=2}^{\lfloor n/m \rfloor} \text{Prob}[\mathcal{Z}_1 > u_n, \mathcal{Z}_k > u_n] \right\} \leq \sum_{i,j=1}^{N_\Theta} \lim_{m \rightarrow \infty} \limsup_{n \rightarrow \infty} \left\{ n \sum_{k=2}^{\lfloor n/m \rfloor} \text{Prob}[E_{i,1} \cap E_{j,k}] \right\}. \quad (6.74)$$

But in view of Lemma B.6,

$$\lim_{m \rightarrow \infty} \limsup_{n \rightarrow \infty} \left\{ n \sum_{k=2}^{\lfloor n/m \rfloor} \text{Prob}[E_{i,1} \cap E_{j,k}] \right\} = 0, \quad \forall i, j. \quad (6.75)$$

and the proof is complete •

From Lemmas B7 and B8, we can finally prove

Theorem 2 - If, for some $0 < \bar{\beta} < \infty$

$$\bar{\rho}_m = o\left(\frac{1}{m^{\bar{\beta}}}\right), \quad (6.76)$$

then the supremum of $\{\mathcal{Z}_k | k = 1, \dots, N_\Delta\}$ is asymptotically Gumbel distributed for $N_\Delta \rightarrow \infty$, viz.:

$$\lim_{N_\Delta \rightarrow \infty} \text{Prob} \left[\max_{k=1, \dots, N_\Delta} \mathcal{Z}_k = \max_{k=1, \dots, N_\Delta} \max_{j=1, \dots, N_\Theta} |Y_{j,k}|^2 \leq \log(N_\Theta N_\Delta) + x \right] = \exp[-\exp(-x)]. \quad (6.77)$$

Proof - The sequence $\{\mathcal{Z}_k\}$ satisfies both conditions #1 and #2, and thus by Lemma B.3

$$\lim_{N_\Delta \rightarrow \infty} \text{Prob} \left[\max_{k=1, \dots, N_\Delta} \mathcal{Z}_k \leq \log(N_\Theta N_\Delta) + x \right] = \lim_{N_\Delta \rightarrow \infty} [F_{\mathcal{Z}_k}(\log(N_\Theta N_\Delta) + x)]^{N_\Delta}. \quad (6.78)$$

The explicit form of the r.h.s. of (6.78), which corresponds to the case where the $\mathcal{Z}_k$ are assumed as independent is as yet unknown, such being the CDF $F_{\mathcal{Z}_k}$. However, by the inclusion-exclusion principle [50]:

$$1 - F_{\mathcal{Z}_k}(x) = N_\Theta \text{Prob}[Z_j > x] - \sum_{i>j} \text{Prob}[Z_i > x, Z_j > x] + \sum_{i>j>h} \text{Prob}[Z_i > x, Z_j > x, Z_h > x] - \dots \quad (6.79)$$

In the limit as $x \rightarrow \infty$, the r.h.s. of (6.79) is infinitesimal. The first term in (6.79) is the principal part. Indeed, for any (non empty) set of integers $\{i_1, i_2, \dots, i_p\}$ different from i and j , and for all x

$$\text{Prob}[Z_i > x, Z_j > x] \geq \text{Prob}[Z_i > x, Z_j > x, Z_{i_1} > x, \dots, Z_{i_p} > x]. \quad (6.80)$$

Furthermore, from Lemma B.5,

$$\text{Prob}[Z_i > x, Z_j > x] \sim \exp(-wx), \quad w > 1, \quad (6.81)$$

while

$$\text{Prob}[Z_j > x] = \exp(-x). \quad (6.82)$$

Hence,

$$\lim_{x \rightarrow \infty} \frac{1 - F_{Z_k}(x)}{1 - \exp[-N_\Theta \exp(-x)]} = \lim_{x \rightarrow \infty} \frac{N_\Theta \exp(-x)}{N_\Theta \exp(-x)} = 1, \quad (6.83)$$

which means that the two distributions $F_{Z_k}(x)$ and $\exp[-N_\Theta \exp(-x)]$ are *right tail equivalent*. Under this assumption, theorem **3.15** in [30] states that the domain of attraction of the two distributions is the same, viz:

$$\lim_{N_\Delta \rightarrow \infty} \{F_{Z_k}[\log(N_\Theta N_\Delta) + x]\}^{N_\Delta} = \lim_{N_\Delta \rightarrow \infty} \{\exp[-N_\Theta \exp(-\log(N_\Theta N_\Delta) - x)]\}^{N_\Delta} = \exp[-\exp(-x)]. \quad (6.84)$$

Letting (6.84) into (6.78) proves the theorem •

Remark - Theorem **2** shows that (uniform) convergence is achieved in the limit $N_\Delta \rightarrow \infty$ at any fixed N_Θ . We add without proof that the larger N_Θ , the faster the convergency rate.

Captions to the Figures

Fig. 1 - Newtonian template bank with lexicographic ordering.

Fig. 2 - Difference between the Gumbel distribution $G^N(x)$ and the cumulative distribution of the whole-bank supremum $\Phi_X^{(N)}(x)$ corresponding to the assumption of statistically independent correlators vs. $x - \log N$ for various values of N . The supremum of the difference is plotted in the inset vs. $\log_2 N$.

Fig. 3 - Difference between the Gumbel distribution $G^{N_\Theta}(x)$ and the cumulative distribution of a single reduced correlator vs. $x - \log N_\Theta$, for several values of N_Θ , and two different values of ρ_M .

Fig. 4 - Comparison among several approximants for the cumulative distribution of a single reduced correlator vs. $x - \log N_\Theta$. Numerical simulation (10^4 realizations).


Fig. 5 - Comparison among several approximants for the cumulative distribution of the whole-bank supremum vs. $x - \log N_\Theta$. Numerical simulation (10^4 realizations).

Fig. 6 - Detection threshold γ corresponding to $\alpha = 10^{-3}$ obtained from different models of the no-signal cumulative distribution of the whole-bank supremum vs. number of reduced templates N_Δ . The dotted-dashed line is the continuous limit, eq. (4.35). Search range $0.2\mathcal{M}_\odot \leq \mathcal{M} \leq 10\mathcal{M}_\odot$, Newtonian waveforms, Ligo-I noise.

Fig. 7 - Minimal match Γ vs. number of reduced templates N_Δ . Search range $0.2\mathcal{M}_\odot \leq \mathcal{M} \leq 10\mathcal{M}_\odot$, Newtonian waveforms, Ligo-I noise.

Fig. 8 - Detectable fractions η (eq. (3.8), solid line) and η_0 (eq. (3.9), dashed line) of potentially observable sources vs. number of reduced templates N_Δ , for several false-alarm levels. Search range $0.2\mathcal{M}_\odot \leq \mathcal{M} \leq 10\mathcal{M}_\odot$, Newtonian waveforms, Ligo-I noise.

Fig. 9 - Detectable fractions η of potentially observable sources, obtained from different models of the no-signal cumulative distribution of the whole-bank supremum vs. number of reduced templates N_Δ , for several false-alarm levels. Search range $0.2\mathcal{M}_\odot \leq \mathcal{M} \leq 10\mathcal{M}_\odot$, Newtonian waveforms, Ligo-I noise.



$$i=1,2,\dots,N_{\Theta}, \quad j=1,2,\dots,N_{\Delta}, \quad Z_{i,j} \rightarrow Z_{i+(j-1)N_{\Theta}}$$

